

FM/DAB+/PLAY-FI STREAMING TUNER

T14





Play-Fi technology and wireless audio streaming



DAB+ tuning



iOS / Android control App



TI 32-bit/ 384kHz Digital to Analog Converter



RDS (Radio Data System) capability for FM broadcasts

This is not your father's tuner. While the T14 can receive classic analogue FM stations, it has also been designed to take advantage of Digital Audio Broadcasts (DAB+), as well as all popular Internet streaming services. That's a lot of options, but Rotel's T14 makes selecting them as simple as the touch of a button. The 30 FM and DAB+ presets provide easy access to all

of your favourite music stations. A near endless supply of music sources are supported by the T14 using the DTS Play-Fi iOS and Android Apps including Spotify, Pandora, Tidal, Rhapsody, Amazon Music, Deezer and more. Your listening options for radio broadcasts have never been more varied or available at such high quality.*





FM/DAB+/PLAY-FI STREAMING TUNER

T14



SPECIFICATIONS

FM Tuner

Usable Sensitivity 22.2 dBf **50dB Quieting Sensitivity** 27.2 dBf (mono)

Signal to Noise Ratio

Mono 65 dBf (at 70 dBf) Stereo 60 dBf (at 70 dBf)

Harmonic Distortion

Mono 0.2% (at 70 dBf) 0.3% (at 70 dBf) Stereo Frequency Response 10Hz - 15kHz, ± 3dB 35 dB / 30 dB **Stereo Separation**

(100Hz/1kHz)

Analog Output 1.4 V

Antenna Input 75 Ohms F connector

DAB Tuner

-80 dBm Sensitivity

Band III (174 - 240MHz) **Tuning Range Audio Data Rate** 224kbps (Max) 20 - 20kHz, +/- 0.2 dB **Frequency Response** 2.1V at 0 dBFS **Analog Output**

Antenna Input 75 Ohms F connector General

Network connection

Security

Power Requirements (AC)

Europe USA **Power Consumption** 16 watts **Standby Power Consumption** < 0.5 watts

Finishes

Dimensions (W x H x D)

Front Panel Height

Weight (net)

802.11 b/g/a/n Dual Band Push button set-up (WPS)

WEP, WPA/WPA2 WPA-PSK/WPA2-PSK

230V, 50Hz 120V, 60Hz

Silver and Black 430 x 93 x 334mm 17" x 3 5/8" x 13 1/8"

80mm, 3 1/8" 5.1 kg, 11.3 lb

